

## Compact, Waterproof Professional CB Radio



MIL-STD  
810G

IP67  
↓ -1m

- ช่องใช้งาน 160 ช่อง ตามมาตรฐาน กสทช.
- ขนาดเล็ก น้ำหนักเพียง 240 กรัม
- กินไฟเพียงนิดเดียว 5 วัตต์ กิน 1.3A
- ช่องย่อยมากกว่า 100,000 ช่อง
- MIL-STD 810G และ IP67
- วงจรหนอมเครื่อง (TOT)
- SCRAMBLER FUNCTION
- DTMF/PAGER-CODE/SQUELCH
- ปุ่ม P0-P3, ปุ่มสีแดง สามารถโปรแกรมฟังก์ชันได้ตามต้องการ
- ลำโพงภายในดังถึง 2500mW

## SPECIFICATIONS

GENERAL	
Frequency range	245.0000-246.9875MHz
No. of operating Ch.	CB 160 channels (Simplex)
Type of emission	FM (8K50F3E)
Antenna impedance	50Ω (BNC)
Operating Temp. range	-30°C to +60°C
Frequency stability	±2.5ppm
Power supply voltage	7.2V DC with supplied battery pack
Current drain (approx.)	
Tx High/Low	1.3A/0.7A (5W/1W)
Rx Max.audio/Standby	500mA/77mA
Dimensions (WxHxD)	52.2x111.8x24.5 mm; 2.06x4.4x0.96 in (Projections not included)
Weight (approx.)	240g ; 8.47 oz (With BP-279)
TRANSMITTER	
Output power (at 7.2V)	5W /1W (High/low)
Max. freq. deviation	±2.5kHz
Spurious emissions	70dB
Adjacent Ch. power	65dB
FM Hum and noise	40dB
Ext. microphone connector	3-conductor 2.5 (d) mm (1/8")/2.2kΩ
RECEIVER	
Intermediate freq.	46.35MHz/450kHz (1st/2nd)
Sensitivity	0.2μV (at 12dB SINAD)
Squelch sensitivity	0.2μV (threshold)
Adjacent Ch. selectivity	65dB
Spurious response	85dB
Intermodulation	75dB
Hum and noise	50dB
Audio output power	2500 mW
Ext. speaker connector	3-conductor 3.5(d)mm(1/8")/8Ω

Measurements made in accordance with EIA/TIA-603.

All stated specifications are subject to change without notice or obligation.

## Applicable U.S. Military Specifications &amp; IP Rating

Standard	MIL 810G	
	Method	Procedure
Low Pressure	500.5	I, II
High Temperature	501.5	I, II
Low Temperature	502.5	I, II
Temperature Shock	503.5	I-C
Solar Radiation	505.5	I
Rain Blowing/Drip	506.5	I, III
Humidity	507.5	II
Salt Fog	509.5	-
Dust Blowing	510.5	I
Immersion	512.5	I
Vibration	514.6	I
Shock	516.6	I, IV

Also meets equivalent MIL-STD-810-C, -D, -E and -F.

## Ingress Protection Standard

Dust & Water	IP67 (Dust-tight and waterproof protection)
--------------	---------------------------------------------

## OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.



Battery packs	Type and capacity	Operating time*
BP-278	Li-Ion, 7.2V 1200mAh	10 hours (Approx.)
BP-279	Li-Ion, 7.2V 1600mAh	14 hours (Approx.)
BP-280	Li-Ion, 7.2V 2450mAh	20 hours (Approx.)

\* Tx: Rx: standby = 5:5:90. Power save function ON.  
Capacity : Typical Spec.

## RAPID CHARGER



## MULTI-CHARGER



## CIGARETTE LIGHTER CABLE &amp; POWER SUPPLY CABLE



\*1 BC-123SA for 120V AC. SE for 230V AC. SV for 240V AC.

## SPEAKER-MICROPHONES



## EARPHONE-MICROPHONES



## HEADSETS



## PTT SWITCH CABLE



## BELT CLIP



## CHARGER BRACKET



## STANDARD ANTENNAS

\* FA-B71V 245-247MHz ANTENNA  
Same as supplied.

## Supplied accessories:

(May differ depending on version)

- Battery pack, BP-279
- Desktop charger, BC-213
- AC adapter, BC-123S
- Belt clip, MB-133
- Antenna



The "3D GENUINE Icom label" is attached to the rear chassis under the battery.  
Check the Icom website for details: <http://www.icom.co.jp/world/genuine-info/>

Icom, Icom Inc. and the Icom logo are registered trademarks of Icom Incorporated (Japan) in the United States, the United Kingdom, Germany, France, Spain, Russia, Japan and/or other countries. All trademarks are the properties of their respective holders.

## Icom Inc.

1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013 URL: <http://www.icom.co.jp/world/index.html>

## Count on us!

## Icom America Inc.

2380 116th Avenue NE,  
Bellevue, WA 98004, U.S.A.  
Phone : +1 (425) 454-8155  
Fax : +1 (425) 454-1509  
E-mail : [sales@icomamerica.com](mailto:sales@icomamerica.com)  
URL : <http://www.icomamerica.com>

## Icom Canada

Glenwood Centre #150-6165 Highway 17,  
Delta, B.C., V4K 5B8, Canada  
Phone : +1 (604) 952-4266  
Fax : +1 (604) 952-0090  
E-mail : [info@icomcanada.com](mailto:info@icomcanada.com)  
URL : <http://www.icomcanada.com>

## Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road,  
Clayton, VIC 3168 Australia  
Phone : +61 (03) 9549 7500  
Fax : +61 (03) 9549 7505  
E-mail : [sales@icom.net.au](mailto:sales@icom.net.au)  
URL : <http://www.icom.net.au>

## Icom New Zealand

146A Harris Road, East Tamaki,  
Auckland, New Zealand  
Phone : +64 (09) 274 4062  
Fax : +64 (09) 274 4708  
E-mail : [inquiries@icom.co.nz](mailto:inquiries@icom.co.nz)  
URL : <http://www.icom.co.nz>

## Icom (Europe) GmbH

Communication Equipment  
Himmelgeister Str. 100,  
D-40225 Düsseldorf, Germany  
Phone : +49 (0211) 346047  
Fax : +49 (0211) 333639  
E-mail : [info@icom-europe.com](mailto:info@icom-europe.com)  
URL : <http://www.icomeurope.com>

## Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer"  
08190, Sant Cugat del Valles, Barcelona, Spain  
Phone : +34 (93) 590 26 70  
Fax : +34 (93) 589 04 46  
E-mail : [icom@icomspain.com](mailto:icom@icomspain.com)  
URL : <http://www.icomspain.com>

## Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay,  
Kent, CT6 8LD, U.K.  
Phone : +44 (01227) 741741  
Fax : +44 (01227) 741742  
E-mail : [info@icomuk.co.uk](mailto:info@icomuk.co.uk)  
URL : <http://www.icomuk.co.uk>

## Icom France s.a.s.

Zac de la Plaine,  
1 Rue Brindejonc des Moulinais, BP 45804,  
31505 Toulouse Cedex 5, France  
Phone : +33 (5) 61 36 03 03  
Fax : +33 (5) 61 36 03 00  
E-mail : [icom@icom-france.com](mailto:icom@icom-france.com)  
URL : <http://www.icom-france.com>

## Icom Polska

Sopot, 3 maja 54, Poland  
Phone : +48 (58) 550 7135  
Fax : +48 (58) 551 0484  
E-mail : [icompolkska@icompolkska.pl](mailto:icompolkska@icompolkska.pl)  
URL : <http://www.icompolkska.com.pl>

## Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road,  
Taipei, Taiwan, R.O.C.  
Phone : +886 (02) 2559 1899  
Fax : +886 (02) 2559 1874  
E-mail : [sales@asia-icom.com](mailto:sales@asia-icom.com)  
URL : <http://www.asia-icom.com>

## Beijing Icom Ltd.

100C7, Long Silver Mansion, No.88, Yong Ding  
Road, Haidian District, Beijing, 100039, China  
Phone : +86 (010) 5889 5391/5392/5393  
Fax : +86 (010) 5889 5395  
E-mail : [bjicom@bjicom.com](mailto:bjicom@bjicom.com)  
URL : <http://www.bjicom.com>

## Your local distributor/dealer:

บริษัท เวิลด์ วาย เรดิโอ จำกัด

9/12,14 หมู่ที่ 3 ตำบลบางม่วง  
อำเภอบางใหญ่ จังหวัดนนทบุรี 11140

โทร : 081-6351458, 02-4033425-7

Email : [world\\_wireradio@hotmail.com](mailto:world_wireradio@hotmail.com)